



**SONESSE® WIREFREE** powered by SOMFY

**Sonesse 28**

A compact, quiet and powerful motor with a built-in, rechargeable battery. Works well for a range of applications, especially shallow windows with minimal depth requirements.



- Adjustable Speed
- RF antenna wire must be exposed, can not come into contact with metal, and may need to be repositioned for optimal range
- A 12V DC charging kit is included, 1 for every 4 shades
- Batteries must be recharged before their complete discharge in order to prevent loss of shade programming due to under voltage. The suggested battery recharging cycle is once per year or when slowing shade operation is observed

**MOTOR SPECIFICATIONS**

Voltage	12V DC
Sound Level*	≤48 dB
RF Control Range (will vary)	60ft
Approximate Lift Capacity**	8lbs

\*According to standards ISO 374 NF 31022 in dB

\*\*For reference only. Specific load capacity for all shades to be determined by H&F

**SHADE SPECIFICATIONS**

Min. Roman Shade Width	24"	
Min. Roman Shade Headrail Depth	2.25"	
Min. Roller Shade Width	23.625"	
	Standard Bracket	Large Bracket
Max. Roller Shade Diameter	3.25"	4.5"

**MOTOR AND BRACKETING DIMENSIONS**

